

RATPAC 12 X 2.4kW SOCAPEX 20 INCH DIMMER CANADA



An incandescent dimmer that also dims 120V LED tubes, featuring our newly redesigned 24 channel controller.



Tried and true design with over-sized solid state relays and rugged breakers. Equipped with rigging, hoisting points. Simple addressing with no menus. Dim/non-dim option with dip switch selections and bump buttons. Stackable design. All Ratpac dimmers are ETL and CSA listed and now include CRMX technology, allowing you control up to a quarter mile range with in line of sight. Transmit or receive with the flip of a switch.

RATPAC 12 X 2.4 kW SOCAPEX 20 INCH DIMMER

INPUT: 120 VAC 3 PHASE E1018 CAMLOK
OUTPUT: 2 SOCAPEX, 12 CHANNELS,
2.4 kW PER CHANNEL

DIMMING DEVICE

480 VAC 40 A SOLID STATE RELAY

OVERLOAD PROTECTION

20 A RESETTABLE BREAKERS

CONTROL

ANALOG: DMX 5 PIN INPUT & OUTPUT XLR
WIRELESS: CRMX RECEIVE OR TRANSMIT
MANUAL BUMP BUTTON, BI-COLOR INDICATED
DIM/NON DIM DIP SWITCHES
SELF-TERMINATING DMX STATUS QUO

DIMENSIONS

8" H x 20" W x 20" D
WEIGHT: 63 LBS

MODEL

756012-CANADA

"QUIET ON SET."