

# RATPAC 3 X 12kW 23 INCH DIMMER CANADA



*An incandescent dimmer that also dims 120V LED tubes, featuring our newly redesigned 24 channel controller.*



Tried and true design with over-sized solid state relays and rugged breakers. Equipped with rigging, hoisting points. Simple addressing with no menus. Dim/non-dim option with dip switch selections and bump buttons.

Stackable design. All Ratpac dimmers are ETL and CSA listed and now include CRMX technology, allowing you control up to a quarter mile range with in line of sight. Transmit or receive with the flip of a switch.

## **RATPAC 3X12 KW 23 INCH DIMMER**

INPUT: 120 VAC 3 PHASE E1018 CAMLOK  
OUTPUT: 120V

### **DIMMING DEVICE**

480 VAC 200 A SOLID STATE RELAY

### **OVERLOAD PROTECTION**

100 A BREAKERS

## **CONTROL**

ANALOG: DMX 5 PIN INPUT & OUTPUT XLR  
WIRELESS: CRMX RECEIVE OR TRANSMIT  
MANUAL BUMP BUTTON, BI-COLOR INDICATED  
DIM/NON DIM DIP SWITCHES  
SELF-TERMINATING DMX STATUS QUO

## **DIMENSIONS**

8" H x 24" W x 20" D  
WEIGHT: 97 LBS

## **MODEL**

900006-12-CANADA



**"QUIET ON SET"**